

S3PC3.8-180-110-1500D

DC Solar Impeller Pump with SSCO Mppt Controller

>> Newly Design MPPT Controller

>> Brushless DC Motor

>> Copper Steel Impel

>> Outlet 1.25 "

Max. Flow 3.8m³/h

Max. Head 180m



Solar panel

Total 8 PCS, 4PCS 300W all in Series, 2 Line In Parallel

Technical Parameter

Voltage	Optimum input voltage(DC)	Power	Max. Flow	Max. Head	Outlet	Cable	Controller	Solar panel Open circuit voltage (VOC)	Solar panel Power	Packing (cm)	Weight (KG)
110V	60-220V	1500W	3.8m ³ /h	180m	1.25 "	2m	SSCO	<250V	Total 8 PCS, 4PCS 300W all in Series, 2 Line In	134L*22W*13H	134L*22W* 13H

SSCO MPPT Controller



Running Speed
Control



Short-Circuit
Protection



MPPT



Dry Running
Protection



Soft Starting
Protection



Reverse Voltage
Protection



Low-voltage /
Over-voltage
Protection



Over Current
Protection

Performance Chart

Head(m)	178.0	165.1	158.5	143.4	122.2	101.0	76.2	45.7	5.9	0.0	0.0	0.0	0.0
Flow(m ³ /h)	0.1	0.5	1.0	1.5	2.1	2.6	3.0	3.5	4.0	0.0	0.0	0.0	0.0

S3PC SSCO Mppt Controller DC Solar Pump

